

Dual-Band Yagi DK7ZB 144/430 MHz 6+10el. 200cm**Price : 95.70 Euro**Catalog No. : **VPA-DK7ZBDB270610**Manufacturer : **VPA-Systems**Availability : **Available - Up to 20 working days production time**

Rating :

Antenna available from:**HogtTelecom - next day shipping****<http://hogttelecom.nl/antenna/dk7zb-antennes/multi-band-yagi>***** NEW !****Dual-Band Yagi DK7ZB 144/430 MHz 6+10el. 200cm**

Dual-Band DK7ZB Yagi antenna. Excellent for FM, SSB and satellites. Single coax feed. It will be perfect addition to dual-bander VHF/ UHF with single VHF/UHF socket like FT-857D or IC-7000.

| Technical information | 2m band | 70cm band |
|-----------------------------------|-----------------------------|------------------|
| Frequency coverage | 144-146 MHz | 430-440 MHz |
| Number of elements | 6 | 10 |
| Gain | 11.5 dBi | 12.4 dBi |
| Fron-to-Back ratio | -18.7 dB | -15.4 dB |
| Vertical pattern width (+/-3dB) | 64° | 72° |
| Horizontal pattern width (+/-3dB) | 52° | 28° |
| Max. power | 300 W | 200 W |
| Max. SWR | 1.5:1 | 1.5:1 |
| Antenna socket | Type N | |
| Match | 1:1 50ohm (Teflon COAX) | |
| Overall length | 201 cm | |
| Cross-Boom | 20x20x1 mm | |
| Elements diameter | 10 mm | |
| Material | aluminium / stainless steel | |
| Mast mount | max. dia. 50 mm | |
| Weight | 1.8 kg | |

When assembled, the antenna is ready to work and does not require additional tuning.**No drilling, no cutting - just assembly and enjoy antenna.**